

# Technical Rider Café Gigant

Last updated: 08-10-2019

Please contact Peter Boekhorst +31 (0) 55 521 63 46

## **Sound:**

### **Front of House:**

- 1x Midas Venice U24 (16 mono / 4 stereo / 6 aux)
- 1x BSS EQ
- 1x KT Square One Dynamics
- 1x TC M-ONE
- 1x TC D-TWO
- 1x Marantz CD-player

### **PA system:**

- 4x Community SLS920
- 2x Pro-One 215 sub
- 2x Pro-One 118 sub
- 2x Lab Gruppe FP3400 Amp

### **Monitoring system:**

- Monitoring from FOH
- 4x Turbosound TFM122M 12" floormonitor

### **Microphones:**

- 8x Shure SM 58
- 4x Shure SM 57
- 3x Shure B57
- 7x Sennheiser e604
- 1x Sennheiser e602
- 3x Sennheiser MD 421
- 1x Sennheiser MD 441
- 2x AKG D112
- 6x AKG condenser microfoon
- 10x BSS DI

## **Light:**

**No specific lighting facilities.**

**When necessary please contact for possibilities**

## **DJ:**

### **Mixers:**

- 1x Pioneer DJM 800

### **CD players:**

- 2x Pioneer CDJ 2000
- 2x Pioneer CDJ 2000 NXS2

### **Turntables:**

- 2x Technics SL 1210 MK2
- 2x Technics SL 1200 MK2



# Technical Rider Café Gigant

## **Power:**

3 x 230V 16A

## **Capacity and Dimensions:**

Capacity: 100 persons  
Stageheight: 30 cm  
Stagewidth: 5 meter  
Stagedepth: 3 meter  
Clearance: 3 meter

## **Contact en Adresses:**

Technical contact: Peter Boekhorst  
Office/café: +31 (0) 55 521 63 46  
Cellphone: +31 (0)6 10 24 47 70  
[p.boekhorst@gigant.nl](mailto:p.boekhorst@gigant.nl)

Visitor address: Nieuwstraat 377  
7311 BR Apeldoorn

Artist Entrance/Parking:  
Museumpassage (via Roggestraat)

## **Note:**

This location is a bar setting and not at all comparable with our pop or theater venue.  
There is limited space for (semi-acoustical) concerts and we maintain a sound pressure limit of 93dB(A) at mixposition.

The logo for Gigant, featuring the word "gigant" in a bold, blue, sans-serif font. The letter "i" is replaced by a stylized graphic of a vertical bar with a horizontal bar at the top, resembling a musical note or a stylized "i". The letters "a" and "n" have small diamond shapes below them.